



Audio & IR Control CAT5 Transceiver Kit

A0304

The A0304 Audio & IR Control CAT5 Transceiver Kit can deliver balanced audio and IR signals over 1,000 feet of CAT5 cable. It's the perfect way to send noise-free audio over cabling that already exists in the home. The decorator style wall plates flush mount into the wall and easily blend into traditional and modern decor. The low cost, simplicity, and availability of CAT5 cable makes the A0304 a convenient choice for both new construction and retrofit applications.

Features

Transport audio from a bedroom back to your main entertainment system

Control the audio device in the bedroom from your entertainment room

Sends line-level audio over 1,000 feet of category cable

Compatible with Category 5, 5E, and 6 wiring

Specifications*

THD + Noise:	<0.2%, 20Hz-20kHz
Signal/ Noise:	>-96dB
Frequency Response:	20Hz-20kHz +/- 0.3dB
Input Impedance:	20K Ohms
Output Impedance:	600 Ohms
Power Requirements:	15VDC @ 0.075A (75mA)
Power Supply:	15VDC @850mA
Wire Type:	4-pair, UTP Category 5, 5e, or 6
Maximum Cable Run:	1,000 feet over CAT5



A0304 Input Wall Plate (Front)



A0304 Output Wall Plate (Front)



A0304 Input Wall Plate (Back)



A0304 Output Wall Plate (Back)

*Specifications subject to change



Channel Vision Central Structured Wiring



Channel Vision IR & Audio Equipment



ARIA™ Multi-Room Audio



Channel Vision Technology Modulators, Cameras, Intercoms