

# A-BUS® 4-Source 4-Zone Kit

## AB-904 / AB-904IA

Channel Vision's AB-904 4-Source, 4-Room A-BUS Kit is an excellent whole-house music solution. It allows up to four different sources to be played in four different zones simultaneously, making it perfect for families with a variety of listening interests. Controlling your music is easy with the P-1044's source specific IR repeating which allows independent control of identical source components. The A0502 remote allows you to easily adjust the volume level on the AB-134 without leaving the comfort of your favorite chair.

(1) P-1044

(1) A0505

(4) IR-3001

(4) AB-134W



(1) J-110-TOOL



### P-1044 Specifications

**Power Supply Voltage :** 24VDC, 3.2A  
**Audio Inputs:** (4) RCA type (L/R Audio), (4) RJ-45  
**Keypad Outputs:** (4) RJ-45, (4) 110 punch down  
**IR Emitter Outputs:** (5) 3.5mm mono jacks  
**Operating Temperature:** -10°C to +50°C  
**Wiring Requirements:** CAT5 or better  
**Dimensions:** 7"W x 6.5"H x 1.5"D

### AB-134 Specifications

**Operating Voltage :** 24VDC 2.3 Amps  
**Cable requirements:** CAT5 or better  
**Speaker impedance:** 6-8 ohm  
**IR repeating:** 30-60kHz  
**IR sensor range:** 40' @ 40kHz, 25' @ 56kHz  
**Operating Temperature:** -10°C to +50°C

Specifications subject to change without notice. Designed in the U.S. Made in Taiwan. Channel Vision Technology, Channel Vision Central and ARIA are trademarks of Channel Vision Technology. Channel Vision™ Technology 2013©. A-BUS is a registered trademark of Leisure Tech Electronics Pty Ltd



Surveillance Systems



Structured Wiring



Intercom & Telephone  
Entry Systems



IR Remote Control  
Distribution



Audio & Video  
Distribution