

A-BUS® 4-Source 4-Zone Kit

AB-904 / AB-904IA

Channel Vision's AB-904 4-Source, 4-Room A-BUS Kit is an excellent whole-house music solution. It allows up to four different sources to be played in four different zones simultaneously, making it perfect for families with a variety of listening interests. Controlling your music is easy with the P-1044's source specific IR repeating which allows independent control of identical source components. The A0502 remote allows you to easily adjust the volume level on the AB-134 without leaving the comfort of your favorite chair.

(1) P-1044

(1) A0505

(4) IR-3001

(4) AB-134W



(1) J-110-TOOL



P-1044 Specifications

Power Supply Voltage : 24VDC, 3.2A
Audio Inputs: (4) RCA type (L/R Audio), (4) RJ-45
Keypad Outputs: (4) RJ-45, (4) 110 punch down
IR Emitter Outputs: (5) 3.5mm mono jacks
Operating Temperature: -10°C to +50°C
Wiring Requirements: CAT5 or better
Dimensions: 7"W x 6.5"H x 1.5"D

AB-134 Specifications

Operating Voltage : 24VDC 2.3 Amps
Cable requirements: CAT5 or better
Speaker impedance: 6-8 ohm
IR repeating: 30-60kHz
IR sensor range: 40' @ 40kHz, 25' @ 56kHz
Operating Temperature: -10°C to +50°C

Specifications subject to change without notice. Designed in the U.S. Made in Taiwan. Channel Vision Technology, Channel Vision Central and ARIA are trademarks of Channel Vision Technology. Channel Vision™ Technology 2013©. A-BUS is a registered trademark of Leisure Tech Electronics Pty Ltd



Surveillance Systems



Structured Wiring



Intercom & Telephone
Entry Systems



IR Remote Control
Distribution



Audio & Video
Distribution