



All-in-One IR Repeater Kit

IR-5011

Channel Vision's IR-5011 All-in-One IR Repeater System utilizes the latest IR technology to perfectly repeat the IR codes of the most popular cable boxes. The IR receiver contains self-modifying software that automatically adjusts to the code of the cable box to ensure reliable IR control. The kit includes the IR receiver, 3 IR emitters, 4 emitter holsters, 1 receiver holster, 3 versatile mounting accessories and a power supply



FEATURES

Perfect repeating with Uverse, Cisco, Scientific Atlanta and Motorola

3 IR Emitters

Status LEDs for power & IR signal indication

Knob to adjust sensitivity on one emitter output.

SPECIFICATIONS*

*Specifications subject to change.

IR Repeater Hub

Power Supply Voltage: 12vDC 500mA Regulated

IR Freq. Range Supported: 36 kHz-60 kHz

Maximum IR receivers: 6

Connecting Block Dimensions: 1.10" x 1.03" x 4.25"

IR Emitter Outputs: 3

Color: Black

IR Receiver

Voltage Requirements: 12vDC 250mA Switching

IR Freq. Range Supported: 36kHz - 60kHz

IR Pickup Range: 40 ft. @ 38kHz, 20 ft. @ 56kHz

IR Receiver Head Dimensions: 0.65" x 0.35" x 0.25"

How IR repeating works

